Aqara

Light Switch H2 Horizontal User Manual

For

Light Switch H2 Horizontal (2 Buttons, 1 Channel)
Light Switch H2 Horizontal (2 Buttons, 2 Channels)
Light Switch H2 Horizontal (4 Buttons, 4 Channels)

Product Introduction

Aqara Light Switch H2 Horizontal is a smart switch based on ThreadZigbee wireless communication protocols which can control the connected lights. It can be used with a neutral wire or in a non-neutral wire setup. The switch supports multiple control modes, including monitoring, power statistics, and other functions. It can also be used with other Aqara devices to create a variety of interconnected control functions.

* This product needs to be used with a device that has Matter Border Router function.

Warnings

1. This product is not a toy. Please keep it away from children.
2. This product is designed for indoor use only.
3. Do not use it in humid environments or outdoors.
4. Do not expose the product to water. Do not spill water or other liquids onto the product.
5. Do not place this product near a heat source. Do not place it in an environment with temperatures above 40°C (104°F).
6. Do not attempt to repair this product by yourself. All repairs should be performed by an authorized professional.
7. Please dispose of this product in accordance with local waste management regulations. The manufacturer is not responsible for any risks or property losses caused by misuse or failure to follow the product instructions.

Installation Method

Light Switch H2 Horizontal (2 Buttons, 1 Channel)

1.Please make sure that the power at the circuit breaker or fuse box is turned off before you begin wiring!

2.Identify the type of electrical circuit in your home. For the 2 button and 1 channel switch, we support three types of circuits:

- Single Pole Wiring
- 3/3-way (light switches two-switch)
- 3/3-way (light between two switches)

Please refer to the following illustrations to determine your home's circuit type and wire it correctly. For the circuit wiring, we recommend seeking assistance from a professional electrician.

* Use only one switch in a 3-way circuit, the other end needs to be a normal standard switch. Both the old and new switch circuits need to be rewired according to the diagram.

* Use only one switch in the power input circuit, the other end needs to be a normal standard switch. Both the old and new switch circuits need to be rewired according to the diagram.

3. Mount the switch unit to the electrical box with the attached screws. Then mount the frame to the switch unit with screws, and attach the faceplate cover to the frame.

4. Turn on the power at the circuit breaker and test the switch by pressing the upper button. If the wired light can be controlled by the upper button, the switch is functioning correctly.

5. In the Aqara Home app, tap Add Accessory, choose Light Switch H2 Horizontal. Scan the Matter QR Code on the paper manual to add the device to the app. The following Quick Setup section will introduce the network configuration methods for both Zigbee and Thread connections.

* Scan the QR code on the paper manual, not on the product. Do not scan the product QR code and scan the QR code on the mounting bracket of the product.

Light Switch H2 Horizontal (2 Buttons, 2 Channels)
Light Switch H2 Horizontal (4 Buttons, 4 Channels)

1.Please make sure that the power at circuit breaker or fuse box is turned off before wiring!

2.For users with Light Switch H2 Horizontal (2 Buttons, 2 Channels) or Light Switch H2 Horizontal (4 Buttons, 4 Channels), please refer to the diagram according to your wiring method. It is recommended to seek assistance from a professional electrician to complete this step.

3. Mount the switch unit to the electrical box with the attached screws. Then mount the frame to the switch unit with screws, and attach the faceplate cover to the frame.

4. Turn on the power at the circuit breaker and test the switch by pressing the upper button. If the wired light can be controlled by the upper button, the switch is functioning correctly.

5. In the Aqara Home app, tap Add Accessory, choose Light Switch H2 Horizontal. Scan the Matter QR Code on the paper manual to add the device to the app. The following Quick Setup section will introduce the network configuration methods for both Zigbee and Thread connections.

* Scan the QR code on the paper manual, not on the product. Do not scan the product QR code and scan the QR code on the metal frame of the product.

Quick Setup

To use the device with a particular Matter ecosystem (Thread Model), a Matter Controller of this ecosystem and a Thread Border Router are required.

1. Double-press any button, then press and hold it for 5 seconds until the green indicator light starts blinking. This indicates that the device is in pairing mode.
2. Open the app that supports Matter, scan the Matter code in the manual or product, or enter the pairing code to add the device to the app.
3. Proceed following the app's instruction.

To use the device in Aqara Home (Thread Model), an Aqara Hub with border router function (for example, Hub M3) is required.

1. Double-press any button, then press and hold it for 5 seconds until the green indicator light starts blinking. This indicates that the device is in pairing mode.
2. In the Aqara Home app, tap Add Accessory, choose Light Switch H2 Horizontal. Scan the Matter code on the manual or product or enter the pairing code to add the device to the app. Select Thread as the network connection method.
3. Proceed following the app's instruction.

To use the device in Aqara Home (Zigbee Model), an Aqara Zigbee Hub is required.

1. Double-press any button, then press and hold it for 5 seconds until the green indicator light starts blinking. This indicates that the device is in pairing mode.
2. Open the app that supports Matter, scan the Matter code in the manual or product, or enter the pairing code to add the device to the app.
3. Proceed following the app's instruction.

Indicator Light Description

Indicator light status	Description
Green solid light for 3 seconds	Device powered on
Green solid light, light flashes twice, then turns off	Pairing/Joining/Device (Thread protocol)
Green solid light, then turns off quickly	Pairing successful
Red solid light for 3 seconds	Device offline
Red indicator light flashes twice	Device voltage is unstable, please connect to a higher voltage power source
Green indicator light flashes quickly	Awaiting device (Zigbee protocol)

Button Description

Button Operation	Function
Double-press, then press and hold for 5 seconds within 2 seconds	Reset the Device Under Pairing
Press any button 10 times continuously	Reset to factory settings
Single Press Mode - Single Press, Double Press, Long Press	Configure and define three Wireless Switch Mode operation mechanisms in Aqara Home (Thread Model)

How to switch from Zigbee protocol to Thread protocol?

1. Install the Aqara Home app and enable Wi-Fi and Bluetooth.
2. Reset the device to factory settings (press any button 10 times continuously to enter network pairing (the first time you add the device) will automatically begin pairing, with its green indicator light flashing quickly).
3. In the Aqara Home app, tap Add Accessory, scan the Matter code on the manual or product, then select Thread as the Switch Protocol page. Proceed by following the app's instruction.

How to switch from Zigbee protocol to Thread protocol?

1. Install the Aqara Home app and enable Wi-Fi and Bluetooth.
2. Reset the device to factory settings (press any button 10 times continuously to enter network pairing (the first time you add the device) will automatically begin pairing, with its green indicator light flashing quickly).
3. In the Aqara Home app, tap Add Accessory, keep the phone close to the device, and Light Switch H2 Horizontal will appear in the app's discovery section at the top left. Tap the icon and select Thread as the Switch Protocol page. Proceed by following the app's instruction.

Product Specifications

Model	Light Switch H2 Horizontal (2 Buttons, 1 Channel)	Light Switch H2 Horizontal (2 Buttons, 2 Channels)	Light Switch H2 Horizontal (4 Buttons, 4 Channels)
Product Name	Light Switch H2 Horizontal (2 Buttons, 1 Channel)	Light Switch H2 Horizontal (2 Buttons, 2 Channels)	Light Switch H2 Horizontal (4 Buttons, 4 Channels)
Model	WS-K13	WS-K23	WS-K43
Wireless Protocols	Thread, Zigbee, Bluetooth		
Dimensions	120 × 86 × 44mm		
Electrical Rating	100-240V~ 50/60Hz 10A Max		
Minimum Power	4W for the load, combined 30W thresold, general condition		
Thread Operation Frequency	2400-2483.5MHz		
Thread Maximum Output Power	4.2 dBm		
Bluetooth Operation Frequency	2400-2483.5MHz		
Bluetooth Maximum Output Power	4.2 dBm		
Operating Temperature	0°C ~ 40°C (32°F ~ 104°F)		
Operating Humidity	5 ~ 95% RH, non-condensation		
What is in the Box	Light Switch H2 Horizontal × 1, Compliance Information × 1, Quick Start Guide × 1, Wire Nut × 2, Wiring Sticker Label × 1		